

# Wired Omni Mic

*"High Quality Omni Mic"*



<b>Model</b>	<b>OS-MIC-1002</b>
Sensitivity	- 33dB $\pm$ 3dB (0dB = 1V / Pa at 1KHz)
Mic Type	Table top Boundary Layer
Operating System	LINUX (Embedded)
Directivity	Unidirectional
Dynamic Range	103dB
Microphone interface (Standard)	XLR 3-pin XLR
Signal to noise ratio	67dB
System indicator	Steady light: power on
Mute switch	Support
Frequency response	30Hz-20kHz
Output impedance	200 $\Omega$ $\pm$ 30% at 1kHz
Power Requirement	9-52V DC (Phantom Power)